

# MAP

25-Sep.-2017

## 0.6

LED 5W | 220-240VAC | 50-60Hz | COB 3-step | incl. power supply

CE IP67 0.3m 38°

3000K | >80CRI | 150lm  
inox

75116314

OPTIONAL  
recessed housing

90012201

## 0.9

LED 8W | 220-240VAC | 50-60Hz | COB 3-step | incl. PS | phase-cut dim

CE IP67 0.3m 38°

3000K | >80CRI | 480lm  
inox

75126414

OPTIONAL  
recessed housing

90012202

## 1.2

LED 12W | 220-240VAC | 50-60Hz | COB 3-step | incl. PS | phase-cut dim

CE IP67 0.3m 38°

3000K | >80CRI | 750lm  
beam angle 38°  
inox

75136414

OPTIONAL  
recessed housing

90012203

## 1.6

LED 15W | 220-240VAC | 50-60Hz | COB 3-step | incl. PS | phase-cut dim

CE IP67 0.3m 38°


3000K | >80CRI | 950lm  
beam angle 38°  
inox

75146414


OPTIONAL  
recessed housing

90012204


## with recessed housing



OPTIONAL (ORDER SEPARATELY)  
recessed housing




## DIMENSIONS



## MOUNTING INSTRUCTION

- Remove the protective foam inside of the MAP.  
Make sure to screw the screws back on, crosswise, to ensure IP67
- Make a hole in the ground according to the prescribed dimensions (of the recessed housing)
- Drainage: we recommend that all exterior groundspots should be installed with a drainage level even when using a recessed housing



## POWER CONNECTION

- Exterior: WATERPROOF Connection



**Remark: Do not open or cut off the Water Stopper on cable.**

- MOUNTING WITH RECESSED HOUSING**

Use the bolts and the nuts to attach the MAP to the recessed housing

**Caution, risk of electric shock**  
The light source of the integrated LED is not replaceable;  
When the light source reaches its end of life the whole luminaire shall be replaced.


**85°** The MAP 0.6 has an auto-recovery thermal fuse. In order to avoid product early failure in some extreme condition; If the internal components reach a temperature of 85°C, the product will switch off and then restart when cooling down.

# MAP

25-Sep.-2017


## without recessed housing

A. Attached to the floor (or wall, for wall mounting)




A. Attached to the floor (or wall, for wall mounting)

- ⑤ Use the screws to attach the MAP to the floor or wall. Make sure to measure correctly so that you can screw onto a hard material. This type of installation is not possible for MAP 0.6



85 The MAP 0.6 has an auto-recovery thermal fuse. In order to avoid product early failure in some extreme condition; If the internal components reach a temperature of 85°C, the product will switch off and then restart when cooling down.

 Caution, risk of electric shock The light source of the integrated LED is not replaceable; When the light source reaches its end of life the whole luminaire shall be replaced.

<b>0.6</b>	
LED 5W   220-240VAC   50-60Hz   COB 3-step   incl. power supply	
CE IP67 0.3m 38°	
3000K   >80CRI   150lm	751163I4
inox	
OPTIONAL recessed housing	90012201

<b>0.9</b>	
LED 8W   220-240VAC   50-60Hz   COB 3-step   incl. PS   phase-cut dim	
CE IP67 0.3m 38°	
3000K   >80CRI   480lm	751264I4
inox	
OPTIONAL recessed housing	90012202

<b>1.2</b>	
LED 12W   220-240VAC   50-60Hz   COB 3-step   incl. PS   phase-cut dim	
CE IP67 0.3m 38°	
3000K   >80CRI   750lm	751364I4
beam angle 38°	
inox	
OPTIONAL recessed housing	90012203



<b>1.6</b>	
LED 15W   220-240VAC   50-60Hz   COB 3-step   incl. PS   phase-cut dim	
CE IP67 0.3m 38°	
3000K   >80CRI   950lm	751464I4
beam angle 38°	
inox	
OPTIONAL recessed housing	90012204

# MAP

25-Sep.-2017


## without recessed housing

B. Rests on the stainless steel borders of the fixture




B. Rests on the stainless steel borders of the fixture

- ⑤ Place the MAP into the hole, no tools needed to fix it into the hole. Just let it rest on the stainless steel borders of the fixture



85 The MAP 0.6 has an auto-recovery thermal fuse. In order to avoid product early failure in some extreme condition; If the internal components reach a temperature of 85°C, the product will switch off and then restart when cooling down.

 Caution, risk of electric shock The light source of the integrated LED is not replaceable; When the light source reaches its end of life the whole luminaire shall be replaced.

<b>0.6</b>	
LED 5W   220-240VAC   50-60Hz   COB 3-step   incl. power supply	
CE IP67 0.3m 38°	
3000K   >80CRI   150lm	751163I4
inox	
OPTIONAL recessed housing	90012201

<b>0.9</b>	
LED 8W   220-240VAC   50-60Hz   COB 3-step   incl. PS   phase-cut dim	
CE IP67 0.3m 38°	
3000K   >80CRI   480lm	751264I4
inox	
OPTIONAL recessed housing	90012202

<b>1.2</b>	
LED 12W   220-240VAC   50-60Hz   COB 3-step   incl. PS   phase-cut dim	
CE IP67 0.3m 38°	
3000K   >80CRI   750lm	751364I4
beam angle 38°	
inox	
OPTIONAL recessed housing	90012203

<b>1.6</b>	
LED 15W   220-240VAC   50-60Hz   COB 3-step   incl. PS   phase-cut dim	
CE IP67 0.3m 38°	
3000K   >80CRI   950lm	751464I4
beam angle 38°	
inox	
OPTIONAL recessed housing	90012204