

# DEEP PETIT ADJ 1.0

05-Jun-2019

## 1.0 LED

**LED** 6W | 350mA | COB 3-step | excl. power supply  
 CE  $\triangleleft$  IP20  $\left( \begin{array}{l} 0.3m \\ \star 34^\circ \\ \odot 35^\circ/35^\circ \\ \downarrow 355^\circ \end{array} \right)$

white texture (wired springs)	153361W_
gold (wired springs)	153361G_
bronze (wired springs)	153361Q_
black texture (wired springs)	153361B_
white texture (blade springs)	153361W_C
black texture (blade springs)	153361B_C

### LIGHT COLOUR

2700K   >90CRI   580lm   18Vf	3
3000K   >90CRI   610lm   18Vf	5
1800-2700K   >95CRI   360lm   15Vf	9

### ALWAYS USE

for power supplies see our catalogue



Wired springs

Blade springs



②



④



①



## DIMENSIONS


Wired springs:

1.0 LED



Blade springs

1.0 LED



## MOUNTING INSTRUCTION

- Put the illuminant in the assembled cover.
- Make a hole in the ceiling according to the prescribed dimensions.
- POWER CONNECTION**


SERIAL CONNECTION - for LED

**Always use POWER SUPPLY according to the specifications of the LED-module**

220-240V



220-240V



- Turn the springs and insert the fixture in the ceiling hole



### CAUTION: NO HOT PLUGGING!

Before connecting the luminaire the converter needs to be disconnected from the power supply. If this instruction is disregarded the luminaire might be damaged or destroyed.



WEVER & DUCRÉ  
LIGHTING

[www.weverducre.com](http://www.weverducre.com)

Wever & Ducre bvba Spinnerijstraat 99/21 8500 Kortrijk

INSTALLATION  
INSTRUCTIONS